

Better than \$1/Mflops sustained: a scalable PC-based parallel computer for lattice QCD

Zoltán Fodor^{1*}, Sándor D. Katz^{2†}, Gábor Papp^{1‡}

⁽¹⁾ *Institute for Theoretical Physics, Eötvös University, Pázmány P. 1/A, H-1117 Budapest, Hungary,*

⁽²⁾ *Deutsches Elektronen-Synchrotron DESY, Notkestr. 85, D-22607, Hamburg, Germany*

11 January, 2002

Abstract

We study the feasibility of a PC-based parallel computer for medium to large scale lattice QCD simulations. The Eötvös Univ., Inst. Theor. Phys. cluster consists of 137 Intel P4-1.7GHz nodes with 512 MB RDRAM. The 32-bit, single precision sustained performance for dynamical QCD without communication is 1510 Mflops/node with Wilson and 970 Mflops/node with staggered fermions. This gives a total performance of 208 Gflops for Wilson and 133 Gflops for staggered QCD, respectively (for 64-bit applications the performance is approximately halved). The novel feature of our system is its communication architecture. In order to have a scalable, cost-effective machine we use Gigabit Ethernet cards for nearest-neighbor communications in a two-dimensional mesh. This type of communication is cost effective (only 30% of the hardware costs is spent on the communication). According to our benchmark measurements this type of communication results in around 40% communication time fraction for lattices upto $48^3 \cdot 96$ in full QCD simulations. The price/sustained-performance ratio for full QCD is better than \$1/Mflops for Wilson (and around \$1.5/Mflops for staggered) quarks for practically any lattice size, which can fit in our parallel computer. The communication software is freely available upon request for non-profit organizations.

1 Introduction

The most powerful computers for lattice gauge theory are industrial supercomputers or special purpose parallel computers (see e.g. [1, 2, 3, 4]). Nevertheless, it is more and more accepted that even off-the-shelf processors (e.g. PC processors) can be used to build parallel computers for lattice QCD simulations [5, 6, 7, 9].

*email: fodor@poe.elte.hu

†on leave from Institute for Theoretical Physics, Eötvös University, Pázmány P. 1/A, H-1117 Budapest, Hungary, email: sandor.katz@desy.de

‡email: pg@ludens.elte.hu

There are obvious advantages of PC based systems. Single PC hardware usually has excellent price/performance ratios for both single and double precision applications. In most cases the operating system (Linux), compiler (gcc) and other software are free. Another advantage of using PC/Linux based systems is that lattice codes remain portable. Furthermore, due to their price they are available for a broader community working on lattice gauge theory. For recent review papers and benchmarks see [10, 11, 12].

Despite the obvious advantages it is not clear how good is the price/performance ratio in medium or large scale lattice QCD applications, for which a large number of processors are needed. Clearly, these multi-processor computer systems dissipate a non-negligible amount of heat. The components should be reliable in order to avoid frequent system crashes. Most importantly, the communication network should be fast and cheap enough in order to keep the good price/performance ratio of the single PCs.

We present our experiences and benchmark results. We show that a parallel system e.g. based on $\mathcal{O}(100)$ PCs can run for several weeks or more without system crashes. The costs for air-conditioning are quite small. Such a system is scalable, it uses nearest-neighbor communication through Gigabit Ethernet cards. The communication is fast enough (consuming 40% of the total time in typical applications) and cheap enough (30% of the total price is spent on the communication). The system can sustain 100-200 Gflops on today's medium to large lattices. This result gives a price/performance ratio better than \$1/Mflops for 32-bit applications (twice as much for 64-bit applications).

Already in 1999 a report was presented [7] on the PC-based parallel computer project at the Eötvös University, Budapest, Hungary. A machine was constructed with 32 PCs arranged in a three-dimensional $2 \times 4 \times 4$ mesh. Each node had two special, purpose designed communication cards providing communication through flat cables to the six neighbors. We used the “multimedia extension” instruction set of the processors to increase the performance. The bandwidth between nodes (16 Mbit/s) was sufficient for physical problems, which needed large bosonic systems¹; however, the communication was far too slow for lattice QCD. Here we report on a system which needs no hardware development and has two orders of magnitude larger communication bandwidth through Gigabit Ethernet cards. Our system is based on PCs, each with a P4-1.7GHz processor and 512 MB RDRAM memory. This system with its Gigabit Ethernet communication represents a good balance between CPU power and network bandwidth. According to our knowledge this is the first scalable parallel computer for lattice QCD with a price/sustained-performance ratio better than \$1/Mflops.

In Section 2 we briefly describe the hardware and discuss its cost. Section 3 deals with the software used by our system, particularly with the C library we developed for communication. In Section 4 we discuss physics issues and present benchmark results based on the MILC code in Section 5. Section 6 contains our conclusions.

2 Hardware

The nodes of our system are almost complete PCs (namely PCs without video cards, floppy- and CD-drives) with four additional Gigabit Ethernet cards. Each node consists of an Intel KD850GB motherboard, Intel-P4-1.7GHz processor, 512 MB RDRAM, 100 Mbit Ethernet card, 20.4 GB IDE HDD and four SMC9452 Gigabit Ethernet cards for the two dimensional communication.

Altogether we have 137 PC nodes. One might use it as one cluster with 128 nodes (or two clusters with 64 nodes or four clusters with 32 nodes) for mass production². Two smaller clusters with 4 nodes are installed for development with or without communication. One additional, single machine is used for compilation, controlling the system and for smaller tests.

¹SU(2)-Higgs model for the finite temperature electroweak phase transition (for simulation techniques see e.g. [8])

²We have 264 SMC9452 cards and our benchmark results were obtained on 64-, 32-, 16-, 8- and 4-node clusters




Figure 1: Illustration of a 64-node cluster. The PC nodes are arranged in a 8×8 two-dimensional torus. Each node is an almost complete PC with four additional Gigabit Ethernet cards. The four Gigabit cards are used to reach the four neighboring nodes through cross-twisted copper Cat5 UTP cables. As indicated, at the boundaries periodic boundary conditions are realized.

After turning the machines on each node boots Linux from its own hard-disk. All nodes can be accessed through a 100 Mbit Ethernet network with switches. The single node (the “main” computer) controls the whole cluster. A simple job-management package has been written to copy the executable code and data to and from the nodes and to execute the programs.

Each motherboard has five PCI slots (32bit/33MHz). One of them is used for the 100Mbit Ethernet card³. These cards are connected to six Ovislink FSH24TX+ 24 port 100 Mbit Ethernet switches. Controlling and copying files from and to the nodes is done through this network. The other PCI slots contain the Gigabit Ethernet cards. Each Gigabit Ethernet card is connected to a Gigabit card of a neighboring node by a cross-twisted copper Cat5 UTP cable. This allows us to perform nearest-neighbor communication. The number of the PCI slots on the motherboard determines the dimensionality of the resulting mesh. In our case there are five slots. Four slots are used for Gigabit communication in four directions, thus in two dimensions (see Figure 1). In principle, we could have used the remaining fifth PCI slot for a third dimension of the mesh, though in this third dimension the mesh would have only two nodes (due to the periodic boundary condition a single connection is enough in this special case). This arrangement results in a $2 \times 8 \times 8$ mesh for 128 nodes. Similarly, other PCI slots can also be used for dimensions with extension of 2 nodes. This idea could result in

³note, that another version of this motherboard is equipped with the 100 Mbit Ethernet interface, thus all five PCI slots can be used for other purposes

meshes e.g. $2 \times 2 \times 2 \times 8$ or $2 \times 2 \times 8$ for five or four PCI slots with Gigabit connections, respectively⁴. The best node-topology for a given lattice can be determined by optimizing the surface to volume ratio of the local sub-lattice. Changing the node topology needs reconnecting the Cat5 UTP cables of the system. This procedure is extremely easy, one person can do it in less than 10 minutes. Note, that presently even 32 or 64 nodes can accommodate fairly large lattices. The topology of e.g. a 64-node system is 8×8 with periodic boundary conditions. Such a cluster is illustrated on Figure 1. Note, that the architecture of the machine is similar to that of the APE machines [1].

We started to use our cluster in October 2001. In this three months we never suffered from a system crash of a running PC due to hardware or OS problems. According to our experiences the system can run for several weeks without needing a reboot (after which we reboot anyhow).

One of the most important advantage of PC-based parallel computers is their exceptional price (for price estimates see e.g. [13], though for $\mathcal{O}(100)$ PCs one can easily reach better prices). In February, 2002 the price of one node including the 100 Mbit Ethernet switches is \$502. The four Gigabit Ethernet cards cost additional \$240 for each node (including the cables, which is less than \$1 for each). The power consumption of one node is 140W. Since the machines dissipate a non-negligible amount of heat, we had to install a cooling system. The costs of the cooling system, when distributed among the individual nodes, resulted in \$13 for one node. Thus, the total node (PC+communication+cooling) price is \$755.

As we will discuss it in Section 4 the typical performance of one node with communication overhead is around 800-900 Mflops for QCD with Wilson (500-600 Mflops with staggered) quarks. Note, that whenever we speak about performance we mean sustained-performance. Comparing these performance results and the above prices we end up with a price/performance ratio better than \$1/Mflops for QCD with Wilson (and around \$1.5/Mflops with staggered) quarks.

There is an important message about our architecture. The key element of a cost effective design is an appropriate balance between communication and the performance of the nodes. As it can be seen we spent more than twice as much on the bare PC (\$515 including cooling) than for the fast Gigabit communication (\$240). These numbers are in strong contrast with Myrinet based PC systems, for which the high price of the Myrinet card exceeds the price of such a PC by a factor of two [14]. Similarly, motherboards with 64bit/66MHz PCI buses are expensive, too. Since even for our Gigabit Ethernet based machine the communication overhead is only around 40% (and in principle could be halved) a faster communication can not speed up significantly the system. Clearly, these ratios result in a far worse price/performance relationship for Myrinet based systems than for our architecture.

As we will see the time needed for the calculation is dominated by memory access. This can not be made better by having faster communication or processor. There are in principle two ways to improve the obtained price/performance ratio for PC-based systems. First of all, one can push the costs of such a system down. This is realized in our case by choosing relatively cheap PC components with the high memory bandwidth RDRAM and a rather cheap communication. Secondly, one might use much faster memory access for a comparable price (e.g. use even faster memory access on the motherboard or put the whole lattice to the cache memory). In this case the faster communication would pay off. Unfortunately, this second option can not be used cost effectively right now.

3 Software

The main operating system of the cluster is SuSE Linux 7.1, being installed on each node, separately. As it was mentioned earlier, the machines are connected via Gigabit Ethernet cards, 4 cards per

⁴note, that having 2 nodes in one dimension does not reduces the communication bandwidth, which is essentially fixed by the PCI bus speed

machine building up a 2 dimensional periodic matrix with 4 neighbors for each node (with computers on the side being connected to the one on the opposite side). The job management is done by the “main” computer through an additional 100 Mbit Ethernet network (see e.g. [7]). This separate PC is where the main part of the program development and compilation is done and only the binary code is copied to the nodes. Communication development is done on a separate small 4-PC cluster.

Nodes have special hostnames indicating their location in the matrix. For the 128-node cluster the names are p00,p01 ... p07,p10,p11 ... pf7. The two hexadecimal digits after the leading p represent the two coordinates of the node within the 16×8 matrix.

In order to take advantage of the Gigabit communication from applications (e.g. C, C++ or Fortran code), a simple C library was written using the standard Linux network interface. Currently, we are using a standard socket based communication with Transmission Control Protocol (TCP) widely used in network applications. Clearly, TCP is much more advanced than our needs for a nearest-neighbor communication. This results in a somewhat large communication overhead. As we discuss it later, the typical measured communication bandwidth in QCD applications is around 400 Mbit/s, which should be compared with the maximal theoretical bandwidth of 1000 Mbit/s and with the 800 Mbit/sec measured bandwidth for large packages. In order to eliminate the overhead due to TCP/IP we are working on a new, more efficient driver.

During the startup period of the connection odd nodes act as clients, while even nodes are the servers (for the node with hostname pxy the parity is defined by the parity of x+y). After the network sockets (one two-way socket per link) are established they are kept open till the end of the program. During the execution of the program the previous “clients” and “servers” act symmetrically, both sending and receiving information to or from the neighboring nodes.

The functions of the library handle the data exchange between the neighbors. They can be summarized as follows (the prefix “gb” refers to Gigabit).

```
int gb_open(int *nodes_x, int *nodes_y)
```

Opens four two-way network sockets to the neighboring nodes. On each node hostnames *dir0* (right), *dir1* (up), *dir2* (down) and *dir3* (left) are defined to the IP address of the appropriate neighboring Ethernet card in the */etc/hosts* file. First, the number of available machines is checked in the two directions and the variables *nodes_x* (left-right) and *nodes_y* (up-down) are set accordingly. On success *gb_open* returns NULL, otherwise -1.

```
int gb_close()
```

Closes all four network sockets. No further communication is possible after this call. On success *gb_close* returns NULL, otherwise -1.

```
int gb_send(int dir, char *buffer, int size)
```

```
int gb_recv(int dir, char *buffer, int size)
```

Sends/receives data to/from the given direction. Directions are 0 (right), 1 (up), 2 (down) and 3 (left). Data are provided through a pointer *buffer* with length *size* in bytes. In case of receive operation *size* is the length of the buffer provided. On success the number of transferred bytes is returned, otherwise the return value is -1.

```
int gb_send_recv(int dir, char *send_buffer, char *recv_buffer int size)
```

A combination of send and receive. Sends data to the given direction and receives from the opposite direction. *send_buffer* and *recv_buffer* are pointers to the data to be sent/received. On success the total number of transferred bytes is returned ($2 \times size$), otherwise the return value is -1. This function expects exactly *size* bytes of data to be received and blocks other operation until the whole amount arrives.

```
int gb_collect(int dir, char *buffer, char *result, int size)
```

Collects data from all the nodes in the direction *dir* to the array *result*. The buffer size should be at least the number of nodes in the given direction multiplied by *size*. The data to be transmitted from the current node is placed in *buffer*. It will be copied to the first *size* bytes in *result* on that node. The data from other nodes will be packed after each other and ordered in *result* by the distance of the originating node in the given direction *dir*. On success the total number of transmitted bytes is returned.

Synchronization can be an important issue for parallel computing. For the presented system it is solved by the architecture itself. Each node uses its own clock and waits until the neighbors provide the necessary data to proceed in the program. Since the Gigabit Ethernet cards have their own memory there is no need to synchronize the “send” and “receive” instructions.

4 Computational requirements for lattice problems

Large scale lattice QCD simulations are focused on a few topics. They might be divided into two computationally different classes.

- a. One of them is full QCD. In this case the most important feature of a parallel computer is its maximal CPU performance in Gflops since most of the time is spent on the updating process. The computational requirements for new theoretical developments are similar to those of full QCD.
- b. The other class is heavy quark phenomenology (quenched or unquenched). In this case not only the CPU performance, but also the memory requirements for the measurements play a very important role.⁵

First we discuss full QCD. Only a small fraction (12-18% for large volumes with Wilson fermions) of our 137-node system’s total nominal performance –0.93 Tflops for single precision and 0.47 Tflops for double precision calculations– can be obtained as a sustained value for full QCD simulations. Before we show the detailed benchmark results it is instructive to discuss some features of the calculations. The basic reason for the relatively small sustained-performance/peak-performance ratio is the memory bandwidth. If the pure computational performance is P , the memory bandwidth is B and the number of accessed bytes per operations in the code is F then the maximal sustained performance we can reach (assuming that memory access and computation is not performed simultaneously) is $P_s = 1/(1/P + F/B)$. The theoretical computational performance is $P = 6.8$ Gflop/s since using the P4 processor’s `sse` instruction set, four single precision operations can be performed in one clock cycle. The maximum bandwidth of the RAMBUS architecture is $B = 3.2$ GB/s. The value of F is 1.27 bytes/flop for Wilson and 1.81 bytes/flop for staggered quarks (cf. [11]). This gives an upper limit for the sustained performances, ≈ 1800 Mflops for Wilson and ≈ 1400 Mflops for staggered quarks. Note, that in both cases P_s is dominated by the term F/B (essentially determined by the memory bandwidth) and not by $1/P$ (fixed by the theoretical computational performance). With careful cache-management one can prefetch the next required data concurrently with calculation. By this technique one increases the maximal performance to $P_s \approx B/F$. This estimate further emphasizes the importance of the memory bandwidth.

Now we discuss the question, how good is the presented PC based parallel computer for heavy quark phenomenology. For this sort of physics problem a important computer issue is the memory requirement for the measurement of a heavy-light form-factor. At present we have 512 Mbytes/node. This gives for the 128 nodes 64 Gbyte, which is the memory of the possibly largest APEmille system of $8 \times 8 \times 32$ [2]). The memory of the presented system can be easily extended. One might have 1.5

⁵We carry out full QCD simulations (staggered quarks at finite temperature and/or chemical potential [17]), thus our presented computer with its memory is somewhat less appropriate for heavy quark phenomenology; however, its memory can be easily extended.




Figure 2: Full QCD performance results on a 64-node cluster. We indicate the node performance (left vertical axis) and the total performance of the 64-node cluster as a function of the spatial extension L_s . The lattice sizes are chosen to be $L_s^3 \times 2L_s$. Squares indicate Wilson, triangles staggered dynamical QCD simulation performances, respectively. The dotted line represents the \$1/Mflops value. Lattices of size $16^3 \times 32$ or smaller fits in the memory of one node. For these lattice sizes single nodes were used without communication. For larger lattices communication was switched on. This resulted in an $\approx 30\%$ reduction of the sustained performances. The inserted scale shows the (effective) machine size as the number of communicating nodes on which the lattice is distributed.

Gbyte/node, which increases the costs by approximately 35%. This gives 200 Gbyte memory for a 128-node cluster. If only two propagators at the time are kept in memory, while the others are stored and reloaded from disks, memory requirements reduce sharply (see e.g. the analysis of the apeNEXT project [2]). Note, that this option needs a high bandwidth to and from the disks. Our measured total disk input/output bandwidth for a 128-node cluster is 1.2 Gbytes/s, thus even very large propagators can be loaded or stored in less than a minute. Due to the usage of the local disks this bandwidth scales with the number of nodes and the required time for input/output remains the same. Combining the above features it is easy to see that with extended memory fairly large lattices, e.g. of the order of $64^3 \cdot 96$ can be studied for heavy quark phenomenology on a 128-node cluster.

5 Performance

In this section we discuss the benchmark results for the full QCD case. Figure 2 gives a summary of these runs. Single precision is used for local variables (gauge links and vectors, see [15]) and dot products are accumulated in double precision. Using double precision gauge links and vectors reduces the performance by approximately 50%. The reason for this reduction is twofold. On the one hand, both the memory access, and the communication between the nodes needs twice as much time; on the other hand, sse2-performance (double precision) is just the half of the sse-performance (single precision). In the simulations the R-algorithm is used [16]. Our results correspond to the full code performances (not only to the conjugate gradient iteration) ⁶.

For benchmarking we started from the MILC Collaboration’s public code [15]. In order to increase the performance of the code we modified the original MILC code by three different techniques.

First of all, we used the “multimedia extension” instruction set of the Intel-P4 processors (note, that the same sse instruction set is now available on Athlon XP processors, too). As we pointed out it in 1999 [7] this capability can accelerate the processor by a large factor (in Ref. [7] we used AMD-K6 processors, which performs 4 operations for each clock cycle by using its multimedia extension). The multimedia extension of the Intel-P4 processor works as a vector unit with 128 bits wide registers, which can be used for arithmetic operations with 2 double precision or 4 single precision numbers. There is a simple way to access these registers, work with them and obtain very good performances (see M. Lüscher’s excellent review [12]). We rewrote almost the whole conjugate gradient part of the program to assembly (including also loops over the lattice and not only elementary matrix operations). No preconditioning was used. The $SU(3)$ matrices and vectors were stored in a format that fits well to the `sse` architecture (see the appendix for details). This way we obtained a speedup factor of ≈ 2 in the performances (similar benchmark results were obtained by e.g. Ref. [18]).

Secondly, an important speedup was obtained by changing the data structure of the original MILC code suggested by S. Gottlieb [19]. The original code is based on the “site major” concept. This structure contains all the physical variables of a given site and the lattice is an array of these structures. Instead of this concept one should use “field major” variables. The set of a given type of variable (e.g. gauge links) of the different sites are collected and stored sequentially. In this case the gauge fields and the vectors are much better localized in the memory. If a cache line contains data not needed for the current site it is most probably some data of a neighboring site, which would be needed soon. Using the original structure this additional data of the next bytes of the “site major” structure is another physical variable, which is most likely not needed by the next calculational steps. Thus, “site major” structure effectively spoils the memory bandwidth, which is one of the most important factors of the performance. Similarly to Ref. [19] by changing the “site major” code to a “field major” one we observed a speedup factor of ≈ 2 in the performances.

The third ingredient of our improvement was a better cache management. The number of successful cache-hits was enhanced by extensive use of the “prefetch” instruction. This technique further increased the sustained performance of the code.

One of the most obvious features of Figure 2 is the sharp drop of the performance when one turns on the communication. The most economic solution is to turn on the communication only if the memory is insufficient for the single-node mode. Smaller lattices can be also studied by using the communication (for instance for thermalization or parameter tuning); however, in these cases the communication overhead increases somewhat. E.g. having twice as large surface/volume ratio than the optimal one on a fixed number of communicating nodes we observed an additional 5-10% reduction of the sustained performance.

⁶For the staggered case the full code has been tested using communication. For the Wilson case the computationally most important $(D_W + m_0)\psi$ is tested with communication. The full Wilson performance is estimated based on $(D_W + m_0)\psi$, the same for staggered quarks $((D_s + m_0)\psi)$ and the total staggered performances.




Figure 3: Sustained staggered performance of a 4-node system as a function of the local lattice volume $V=L_s^3 \times L_s/2$ (lower panel). The node topology is 2×2 , thus the total lattice volume is $L_s^3 \times 2L_s$. The two almost parallel lines represent the results obtained by a myrinet system (upper line; these tests were performed on the myrinet cluster of the DESY Theory group, Hamburg) and by our gigabit communication (lower line). The one-node performance is also shown by the almost horizontal line with stars. Clearly, communication is of no use if the one-node performance is better than the 4-node one. Thus, the useful region is given by local lattices $8^3 \times 4$ or larger. The relative difference between the performances of the myrinet and gigabit systems is shown by the upper panel. As it can be seen in the useful region the relative difference is always less than 12%.

It is instructive to study the question, how the communication overhead can be reduced. We needed more than 1 node when lattices of $18^3 \cdot 36$ or larger were studied. With a somewhat better memory allocation lattices of $20^3 \cdot 40$ can still fit in 1 node. In this case the volume/surface ratio of the local sub-lattice gets better resulting in a better communication overhead (e.g. in this case one would obtain 30% instead of 35%, which is slightly better). The typical measured communication bandwidth in QCD applications was around 400 Mbit/s. This is far less than the maximal theoretical bandwidth of 1000 Mbit/s. Since we are using the most straightforward communication based on TCP/IP it is feasible that a more effective driver can reach a bandwidth around 800 Mbit/sec. In this case the communication overhead would be around 20%.

There is a simple theoretical consideration⁷ to describe the performance of our architecture as $P(V, A) = P_0(V)/(1 + c \cdot A/V)$, where P_0 is the performance without communications for a given local lattice volume V on each node. A is the number of “surface” lattice sites (per node) which

⁷we thank our referee for this transparent interpretation

participate in the communication. If each node holds $L_x \cdot L_y$ lattice sites in the communication plane one has $A/V = 2(L_x + L_y)/(L_x \cdot L_y)$, which becomes $A/V = 4/\sqrt{N_p}/L_s$ if the $L_s^3 \cdot 2L_s$ lattice can be distributed in an optimal way ($L_x = L_y$) over the 2-dimensional array of N_p processors. Considering only a limited range of local lattice volumes the variation of $P_0(V)$ due to cache effects is negligible. From the points for $L_s=12, \dots, 16$ in Figure 2 one can read off a value $P_0 \approx 1.63$ Gflops. The above formula for $P(V, A)$ reproduces all measured values shown in Figure 2 for $L_s \geq 12$ with an accuracy of a few percent using $c=1.55$.

Note, that the "simulation scale" of a given physics problem depends on the lattice size used plus the CPU cost to obtain a certain result. The communication overhead of the present architecture is relatively large, i.e. even in the optimal case (the local lattice is large, occupying the whole memory) it is 30–40%. Taking smaller local lattices the sustained performance further drops. According to Figure 3 taking local volumes, which are 80 times smaller than the maximal ones results in an additional 50% drop in the sustained performance. When one uses the system as a scalable one and simulates relatively small local lattices this additional 50% reduction should be also taken into account.

6 Conclusion

We have presented a description of the status of our PC-based parallel computer project for lattice QCD. Nearest-neighbor communication is implemented in a two-dimensional mesh. Communication goes through Gigabit Ethernet cards. Some details of the communication software have been given. Presently, we work on a better driver to increase the communication bandwidth (in this way we expect to half the communication overhead). As it is usual for many PC clusters for our system it is also advisable to put sub-lattices on a relatively small number of nodes. In this case one simulates several independent smaller lattices in parallel. Using this technique one reaches an optimum for the surface to volume ratio and minimizes the time fraction for communication. For larger lattices the whole system should be used.

The saturated dynamical QCD sustained performance of a 128 node system with communication is around 70 Gflops for staggered quarks and 110 Gflops for Wilson quarks (these numbers can be seen as a sort of average performances for typical applications using subsystems with different node numbers and relatively large local lattices; see Figures 2,3).

Finally, we would like to emphasize that the system presented here

1. is a scalable parallel computer with nearest-neighbor communication,
2. can be assembled using standard PC components,
3. takes advantage of the free software environment,
4. has a very good price/sustained-performance ratio for full lattice QCD (with Wilson quarks less than \$1/Mflops, for staggered quarks \$1.5/Mflops),
5. due to its large memory and its large total disk bandwidth it can be used for heavy quark phenomenology.

7 Acknowledgment

We thank F. Csikor and Z. Horváth for their continuous help. We thank them and J. Kuti, Th. Lipert, I. Montvay, K. Schilling, H. Simma and R. Tripicciono for suggestions and careful reading of the manuscript. The benchmark tests were done by modifying the MILC Collaboration's public code (see <http://physics.indiana.edu/~sg/milc.html>). This work was supported by Hungarian Science Foundation Grants under Contract Nos. OTKAT37615T34980/T29803/T22929M37071/OM-MU-708/IKTA111/FKFP220/00.

A Example source code

The following source code demonstrates the usage of sse instructions and communication.

```
/*
 *
 * File: example.c
 * Get SU(3) vectors from neighbors, multiply them by the
 * local links and add the result
 *
 */
*****/

#include<stdio.h>
#include<stdlib.h>
#include"gb_lib.h"

#define DIR_RIGHT 0
#define DIR_UP 1
#define DIR_DOWN 2
#define DIR_LEFT 3

/* su3 vector conveniently aligned for sse operations a_r[3] and a_i[3]
are used only to maintain alignment */
typedef struct{
    float a_r[4];
    float a_i[4];
} sse_su3_vector __attribute__((aligned (16)));

/* su3 matrix */
typedef struct{
    sse_su3_vector e[3];
} sse_su3_matrix __attribute__((aligned (16)));

void sse_mult_su3_mat_vec(sse_su3_matrix *u, sse_su3_vector *src,
                        sse_su3_vector *dest);
void sse_add_su3_vec(sse_su3_vector *v1, sse_su3_vector *v2,
                    sse_su3_vector *dest);

void init_links(sse_su3_matrix *link){
    /* Link initialization code may come here */
}

void init_vec(sse_su3_vector *link){
    /* Vector initialization code may come here */
}

int main(int argc, char *argv[]){

    static sse_su3_vector vect __attribute__((aligned (16)));
    static sse_su3_vector temp1 __attribute__((aligned (16)));
```

```

static sse_su3_vector temp2    __attribute__((aligned (16)));
static sse_su3_vector temp3    __attribute__((aligned (16)));
static sse_su3_vector temp4    __attribute__((aligned (16)));
static sse_su3_vector res      __attribute__((aligned (16)));
static sse_su3_matrix link[2]  __attribute__((aligned (16)));

int nodes_x,nodes_y;

/* Open communication channels */
if (gb_open(&nodes_x,&nodes_y)!=0) {
    printf("Unable to open Gigabit communication channels\n");
    exit(-1);
}
printf("Machine topology: %d x %d nodes\n",nodes_x,nodes_y);
/* Initialize links and vector */
init_links(link);
init_vec(&vect);

/* Get vectors from neighbors */
gb_send_recv(DIR_LEFT,(char *)&vect,(char *)&temp1,
             sizeof(sse_su3_vector));
gb_send_recv(DIR_DOWN,(char *)&vect,(char *)&temp2,
             sizeof(sse_su3_vector));

/* Perform multiplication with links */
sse_mult_su3_mat_vec(&(link[0]),&temp1,&temp3);
sse_mult_su3_mat_vec(&(link[1]),&temp2,&temp4);
sse_add_su3_vec(&temp3,&temp4,&res);
gb_close();
return(0);
}

```

```

;*****
;
;                               *
;           File su3_sse.asm    *
; SU(3) matrix-vector multiplication and vector addition *
;           Compile with nasm v0.98    *
;                               *
;*****

```

```

BITS 32
GLOBAL sse_mult_su3_mat_vec
GLOBAL sse_add_su3_vec

```

```

REAL    equ 0
IMAG    equ 16

```

```

C0      equ 0

```

```

C1      equ 32
C2      equ 64

; SU(3) matrix-vector multiplication
; C prototype:
;
; void sse_mult_su3_mat_vec(sse_su3_matrix *u, sse_su3_vector *src,
;                           sse_su3_vector *dest);
; dest=u*src

sse_mult_su3_mat_vec:
    mov eax,[esp+04h]
    mov ecx,[esp+08h]
    mov edx,[esp+0ch]
    prefetcht0 [eax]
    movaps xmm6,[ecx+REAL]      ; first element of the vector
    movaps xmm7,[ecx+IMAG]
    shufps xmm6,xmm6,00000000b ; real part in xmm6
    shufps xmm7,xmm7,00000000b ; imaginary part in xmm7
    movaps xmm4,[eax+C0+REAL]   ; first column of the matrix
    movaps xmm5,[eax+C0+IMAG]   ; to (xmm4,xmm5)
    movaps xmm0,xmm4           ; complex multiplication
    mulps xmm0,xmm6
    movaps xmm2,xmm7
    mulps xmm2,xmm5
    subps xmm0,xmm2            ; real part goes to xmm0
    movaps xmm1,xmm4
    mulps xmm1,xmm7
    mulps xmm5,xmm6
    addps xmm1,xmm5            ; imaginary part goes to xmm1
    movaps xmm6,[ecx+REAL]     ; second element of the vector
    movaps xmm7,[ecx+IMAG]
    shufps xmm6,xmm6,01010101b
    shufps xmm7,xmm7,01010101b
    movaps xmm4,[eax+C1+REAL]   ; second column of the matrix
    movaps xmm5,[eax+C1+IMAG]
    movaps xmm2,xmm4
    mulps xmm2,xmm6
    addps xmm0,xmm2
    movaps xmm2,xmm7
    mulps xmm2,xmm5
    subps xmm0,xmm2            ; real part added to xmm0
    mulps xmm4,xmm7
    addps xmm1,xmm4
    mulps xmm5,xmm6
    addps xmm1,xmm5            ; imaginary part added to xmm1
    movaps xmm6,[ecx+REAL]     ; third element of the vector
    movaps xmm7,[ecx+IMAG]
    shufps xmm6,xmm6,10101010b

```

```

shufps xmm7,xmm7,10101010b
movaps xmm4,[eax+C2+REAL] ; third column of the matrix
movaps xmm5,[eax+C2+IMAG]
movaps xmm2,xmm4
mulps xmm2,xmm6
addps xmm0,xmm2
movaps xmm2,xmm7
mulps xmm2,xmm5
subps xmm0,xmm2 ; real part added to xmm0
mulps xmm4,xmm7
addps xmm1,xmm4
mulps xmm5,xmm6
addps xmm1,xmm5 ; imaginary part added to xmm1
movaps [edx+REAL],xmm0 ; store the result to dest
movaps [edx+IMAG],xmm1
ret

```

```

; SU(3) vector addition
; C prototype:
;
; void sse_add_su3_vec(sse_su3_vector *v1, sse_su3_vector *v2,
;                      sse_su3_vector *dest);
; dest=v1+v2

```

```

sse_add_su3_vec:
    mov eax,[esp+04h]
    mov ecx,[esp+08h]
    mov edx,[esp+0ch]
    movaps xmm0,[eax+REAL] ; real parts
    movaps xmm1,[eax+IMAG] ; imaginary parts
    addps xmm0,[ecx+REAL]
    addps xmm1,[ecx+IMAG]
    movaps [edx+REAL],xmm0
    movaps [edx+IMAG],xmm1
    ret

```

References

- [1] See e.g. N. Avico et al., Comput. Phys. Commun. 57 (1989) 285; F. Aglietti et al., Nucl. Instrum. Meth. A389 (1997) 56; A. Bartonoli et al., Nucl. Phys. (Proc. Suppl.) 60 (1998) 237; R. Alfieri et al., *ibid* 94 (2001) 846; A. Bartoloni et al., hep-lat/0110153; F. Bodin et al., hep-lat/0110197; R. Tripiccone, Comp. Phys. Comm. 139 (2001) 55; <http://www.pi.infn.it/ape/>, <http://www-zeuthen.desy.de/ape/>
- [2] R. Alfieri et al., hep-lat/0102011.
- [3] Y. Iwasaki, Nucl. Phys. (Proc. Suppl.) 34 (1994) 78 [hep-lat/9401030]; A. Ukawa, *ibid* 42 (1995) 194 [hep-lat/9412106]; Y. Iwasaki, *ibid* 53 (1997) 1007 [hep-lat/9608148]; *ibid* 60 (1998) 246 [hep-lat/9709055]; S. Aoki et al., hep-lat/9903001; T. Yoshie, Comp. Phys. Comm. 142 (2001) 36; <http://www.rccp.tsukuba.ac.jp>.
- [4] I. Arsenin et al, Nucl. Phys. (Proc.Suppl.) 34 (1994) 820; *ibid* 42 (1995) 902 [hep-lat/9412093]; hep-lat/9509075; D. Chen et al., Nucl. Phys. (Proc.Suppl.) 60 (1998) 241; *ibid* 63 (1998) 997 [hep-lat/9709135]; *ibid* 73 (1999) 898 [hep-lat/9810004]; *ibid* 94 (2001) 825 [hep-lat/0011004]; P.A. Boyle et al., hep-lat/0110124; <http://phys.columbia.edu/~cqft>.
- [5] N. Eicker et al., Nucl. Phys. (Proc. Suppl.) 83 (2000) 798 [hep-lat/9909146].
- [6] <http://www-ctp.mit.edu/~negele/LRP/index.htm>
- [7] F. Csikor et al., Comp. Phys. Comm. 134 (2001) 139 [hep-lat/9912059].
- [8] Z. Fodor et al., Nucl. Phys. B439 (1995) 147; F. Csikor et al., Phys. Lett. B357 (1995) 156, Nucl. Phys. B474 (1996) 421; Phys. Rev. Lett. 82 (1999) 21.
- [9] X.Q. Luo et al., cs.DC/0109004.
- [10] N. Christ, Nucl. Phys. (Proc. Suppl.) 83 (2000) 111 [hep-lat/9912009].
- [11] S. Gottlieb, Nucl. Phys. (Proc. Suppl.) 94 (2001) 833 [hep-lat/0011071].
- [12] M. Lüscher, hep-lat/0110007.
- [13] <http://www.pricewatch.com>
- [14] <http://www.myricom.com>
- [15] <http://physics.indiana.edu/~sg/milc.html>.
- [16] S. Gottlieb et al. Phys. Rev. D35 (1987) 2531.
- [17] Z. Fodor and S.D. Katz, hep-lat/0104001, hep-lat/0106002.
- [18] M. Di Pierro, hep-lat/0110116.
- [19] S. Gottlieb, hep-lat/0112026, hep-lat/0112038, hep-lat/0112039.